Read Me First (625-0471-000)

24 Fast Ethernet + 2 Gigabit L2 Managed Switch Packing List :

Before you start installing this L2 Managed Switch, please verify that the package contains the following items:

- 24 Port 10/100Mbps UTP + 2 Port Gigabit Dual Media L2 Managed Switch
- AC Power Cord
- Mounting Accessory (for 19” Rack Shelf)
- User’s Guide CD-ROM
- RS-232 Null Modem Cable

Please notify your sales representative immediately if any of the aforementioned items is missing or damaged.

Power Requirements : AC Line

Voltage	:	100~240 VAC
Frequency	:	50~60 Hz
Consumption	:	15W

Quick Installation :

1. Install the switch in the rack with mounting accessory.
2. Connect the switch to an AC power source.
3. The port 1–24 connector is RJ-45 jack on the switch. Use Category 5 UTP cable to connect between the switch and end station.
4. The port 25, 26 includes two types of media --- TP and SFP/GBIC fiber module; they support TP or fiber with auto-detected function.
5. Use RS-232 interface to pre-configure the switch for network management.
   For example: IP address, VLAN, Port Trunking, STP, etc.

The switch’s serial port default settings are listed as follows:

Baud rate	57600
Stop bits	1
Data bits	8
Parity	N
Flow control	none

The default values of the L2 Managed Switch are as follows:

IP Address	: 192.168.1.1
Subnet Mask	: 255.255.255.0
Default Gateway	: 192.168.1.254
Username	: admin
Password	: admin

User also can use telnet or web to pre-configure the switch with the default IP address and username/password in the first configuration. Please refer to User’s Guide contained in CD-ROM for details on the setting of parameters. User’s manual is filed under the path: \manual of the CD-ROM.